



6A7S

6A6
6A7
6A8
6A9
6A10
6A11
6A12
6A13
6A14
6A15
6A16
6A17
6A18
6A19
6A20
6A21
6A22
6A23
6A24
6A25
6A26
6A27
6A28
6A29
6A30
6A31
6A32
6A33
6A34
6A35
6A36
6A37
6A38
6A39
6A40
6A41
6A42
6A43
6A44
6A45
6A46
6A47
6A48
6A49
6A50
6A51
6A52
6A53
6A54
6A55
6A56
6A57
6A58
6A59
6A60
6A61
6A62
6A63
6A64
6A65
6A66
6A67
6A68
6A69
6A70
6A71
6A72
6A73
6A74
6A75
6A76
6A77
6A78
6A79
6A80
6A81
6A82
6A83
6A84
6A85
6A86
6A87
6A88
6A89
6A90
6A91
6A92
6A93
6A94
6A95
6A96
6A97
6A98
6A99
6A100

PENTAGRID CONVERTER RENEWAL TYPE FOR MAJESTIC RECEIVERS

Heater ■	Coated Unipotential Cathode	
Voltage	6.3	a-c or d-c volts
Current	0.3	amp.
Overall Length	4-9/32" to 4-17/32"	
Seated Height	3-21/32" to 3-29/32"	
Maximum Diameter (without shield)	1-9/16"	
Bulb (with form-fitting shield)	ST-12	
Cap	Small Metal	
Base ▲ *	Small 7-Pin	

■ In circuits where the cathode is not directly connected to the heater, the potential difference between heater and cathode should be kept as low as possible.

▲ Requires a different socket than the medium 7-pin base.

* Basing arrangement is the same as for the 6A7, except that the external shield on the 6A7S is connected to cathode.

Typical Operating Conditions and Curves for the 6A7S are the same as for Type 6A8.



6A8, 6A8-G, 6A8-GT PENTAGRID CONVERTER

Heater ■	Coated Unipotential Cathode		
Voltage	6.3	a-c or d-c volts	
Current	0.3	amp.	
Direct Interelectrode Cap. °	6A8	6A8-G	6A8-GT
Grid #4 to Plate	0.06	0.26	0.26 μμf
Grid #4 to Grid #2	0.1	0.19	0.19 μμf
Grid #4 to Grid #1	0.09	0.16	0.16 μμf
Grid #1 to Grid #2	0.8	1.1	1.1 μμf
Grid #4 to All Other Electrodes (R-F Input)	12	9.5	9.5 μμf
Grid #2 to All Other Electrodes Except Grid #1 (Osc. Output)	5	4.6	4.6 μμf
Grid #1 to All Other Electrodes Except Grid #2 (Osc. Input)	6.5	6	6 μμf
Plate to All Other Electrodes (Mixer Output)	12	12	12 μμf
Overall Length	{ 3-1/8" max.	{ 4-7/32" to 4-15/32"	{ 3-5/16" max.
Seated Height	{ 2-9/16" max.	{ 3-21/32" to 3-29/32"	{ 2-3/4" max.
Maximum Diameter	1-5/16"	1-9/16"	1-5/16"
Bulb	Metal Shell, MT-8	ST-12	T-9
Cap	Miniature	Skirted Min.	{ Skirted Min. Style C

■ In circuits where the cathode is not directly connected to the heater, the potential difference between heater and cathode should be kept as low as possible.

° With shell of 6A8 connected to cathode, and with close-fitting shield on 6A8-G and 6A8-GT connected to cathode.

← Indicates a change.

Dec. 1, 1941

RCA RADITRON DIVISION
RCA MANUFACTURING COMPANY, INC.

DATA

6A8
6A8-G
6A8-GT




6A8, 6A8-G, 6A8-GT

PENTAGRID CONVERTER

(continued from preceding page)

	6A8	6A8-G	6A8-GT
Base	{Small Wafer Octal 8-Pin	{Small Shell Octal 8-Pin	{Small Wafer Octal 8-Pin, Sleeve
Basing Designation	8A	G-8A	GT-8A
Pin 1	{6A8, Shell 6A8-G, No Con. 6A8-GT, Base Sleeve		Pin 5 - Grid #1
Pin 2 - Heater			Pin 6 - Grid #2
Pin 3 - Plate			Pin 7 - Heater
Pin 4 - Grids #3 & #5			Pin 8 - Cathode
Mounting Position			Cap - Grid #4



BOTTOM VIEW

CONVERTER SERVICE

Plate Voltage		300 max. volts
Screen (Grids #3 & #5) Voltage		100 max. volts
Screen Supply Voltage		300 max. volts
Anode-Grid (Grid #2) Voltage		200 max. volts
Anode-Grid Supply Voltage*		300 max. volts
Control-Grid (Grid #4) Voltage		0 min. volts
Plate Dissipation		1.0 max. watt
Screen Dissipation		0.3 max. watt
Anode-Grid Dissipation		0.75 max. watt
Total Cathode Current		14 max. ma.
Typical Operation:		
Plate Voltage	100	250 volts
Screen Voltage	50	100 volts
Anode-Grid Voltage	100	- volts
Anode-Grid Supply Voltage	-	250* volts
Control-Grid Voltage	-1.5	-3 volts
Osc.-Grid (Grid #1) Resistor	50000	50000 ohms
Plate Resistance	0.6	0.36 approx. ohms
Conversion Transconductance	360	550 μ mhos
Conver. Transcond. (approx.) with Control-Grid Bias of -20 volts	3	- μ mhos
Conver. Transcond. (approx.) with Control-Grid Bias of -35 volts	-	6 μ mhos
Plate Current	1.1	3.5 ma.
Screen Current	1.3	2.7 ma.
Anode-Grid Current	2	4 ma.
Oscillator-Grid Current	0.25	0.4 ma.
Total Cathode Current	4.6	10.6 ma.

NOTE: The transconductance of the oscillator portion (not oscillating) is 1150 micromhos under the following conditions: plate volts, 250; screen volts, 55; control-grid volts, -2; anode-grid volts, 100; and oscillator-grid volts, -1.

* Anode-grid supply voltages in excess of 200 volts require use of 20000-ohm voltage-dropping resistor by-passed by 0.1 μ f condenser.

For Typical Circuit and Coil Design Details, refer to Type 2A7.

← Indicates a change.



6A8

6A8

OPERATION* CHARACTERISTICS WITH 50000-OHM OSCILLATOR-GRID LEAK

