



82



82

FULL-WAVE MERCURY-VAPOR RECTIFIER

Filament	Coated	
Voltage	2.5	a-c volts
Current	3.0	amp.
Maximum Overall Length		4-11/16"
Maximum Seated Height		4-1/16"
Maximum Diameter		1-13/16"
Bulb		ST-14
Base		Medium 4-Pin
Pin 1 - Filament		Pin 3 - Plate #1
Pin 2 - Plate #2		Pin 4 - Filament
Mounting Position		Vertical, base down



BOTTOM VIEW (4C)

FULL-WAVE RECTIFIER

Peak Inverse Voltage	1550 max. volts
Peak Plate Current per Plate	600 max. ma.
Condenser Mercury Temperature Range	24° - 60°C
<i>With Condenser-Input Filter:</i>	
A-C Plate Voltage per Plate (RMS)	450 max. volts
Total Effective Plate-Supply Impedance per Plate [▲]	50 min. ohms
D-C Output Current	115 max. ma.
<i>With Choke-Input Filter:</i>	
A-C Plate Voltage per Plate (RMS)	550 max. volts
Input-Choke Inductance	6 min. henries
D-C Output Current	115 max. ma.
Tube Voltage Drop	15 approx. volts

HALF-WAVE RECTIFIER

As a half-wave rectifier, the 82 is operated with plates connected in parallel. Two 82's so connected in a full-wave circuit can supply twice the output current of a single tube. Both plates within the same tube should be connected to the same terminal of the plate transformer. To equalize the current distribution between plates, a resistor of not less than 100 ohms should be connected in series with each plate.

[▲] When a filter-input condenser larger than 40 μ f is used, it may be necessary to use more plate-supply impedance than the minimum value shown to limit the peak plate current to the rated value.

← Indicates a change.

Sept. 2, 1941

RCA RADOTRON DIVISION
RCA MANUFACTURING COMPANY, INC.

DATA