



6AV6

6AV6

TWIN DIODE—HIGH-MU TRIODE

7-PIN MINIATURE TYPE

GENERAL DATA

Electrical:

Heater, for Unipotential Cathode:

Voltage (AC or DC) $6.3 \pm 10\%$ volts

Current 0.3 amp

Direct Interelectrode Capacitances:

	Without External Shield	With External Shield ^o
--	-------------------------------	---

Triode Unit:

Grid to plate 2 μf Grid to cathode and heater . . . 2.2 μf Plate to cathode and heater . . . 0.8 μf Diode-No.2 plate to triode grid . 0.04 max. 0.04 max. μf Characteristics, Class A₁ Amplifier (Triode Unit):

Plate Voltage 100 250 volts

Grid Voltage -1 -2 volts

Amplification Factor 100 100

Plate Resistance (Approx.) 0.08 0.0625 megohm

Transconductance 1250 1600 μmhos

Plate Current 0.5 1.2 ma

Mechanical:

Operating Position Any

Maximum Overall Length 2-1/8"

Maximum Seated Length 1-7/8"

Length, Base Seat to Bulb Top (Excluding tip) . 1-1/2" $\pm 3/32$ "

Diameter 0.650" to 0.750"

Dimensional Outline See General Section

Bulb T5-1/2

Base Small-Button Miniature 7-Pin (JEDEC No. E7-1)


Basing Designation for BOTTOM VIEW 7BT

Pin 1—Triode Grid

Pin 2—Cathode

Pin 3—Heater

Pin 4—Heater

Pin 5—Diode Plate
No. 2Pin 6—Diode Plate
No. 1

Pin 7—Triode Plate

TRIODE UNIT — AMPLIFIER — Class A₁

Maximum Ratings, Design-Maximum Values:

PLATE VOLTAGE 330 max. volts

GRID VOLTAGE:

Positive-bias value 0 max. volts

PLATE DISSIPATION 0.55 max. watt

← Indicates a change.

6AV6



6AV6

TWIN DIODE—HIGH-MU TRIODE

PEAK HEATER-CATHODE VOLTAGE:

Heater negative with respect to cathode. 200 max. volts
 Heater positive with respect to cathode. 200[▲] max. volts

Typical Operation as Resistance-Coupled Amplifier:

*See RESISTANCE-COUPLED AMPLIFIER CHART No. 25
 at front of this Section*

DIODE UNITS — Two

→ Maximum Ratings, *Design-Maximum Values:*

PLATE CURRENT (For each diode) 1 max. ma

→ Characteristics:

Values are for Each Unit

Plate Current for plate volts = 10 2 ma

Diode Considerations:

Consideration of these units, including typical circuits and diode curves, is given at the front of this Section. Diode biasing of the triode unit of the 6AV6 is not suitable.

⁰ With external shield JEDEC No. 316 connected to cathode.

[▲] The dc component must not exceed 100 volts.

Curves for the triode unit of the 6AV6 are the same as those shown for Type 12AX7

→ Indicates a change.