



7AF7

MEDIUM-MU TWIN TRIODE

7AF7
7AG7

Heater, for Unipotential Cathode:

Voltage. 6.3[□] ac or dc voltsCurrent. 0.3^{□□} amp*The 7AF7 is the same as the 14AF7 except for heater rating.*

□ Nominal voltage = 7.0 volts.

□□ Nominal current = 0.32 ampere.

7AG7

SHARP-CUTOFF PENTODE

GENERAL DATA**Electrical:**

Heater, for Unipotential Cathode:

Voltage. 6.3[□] ac or dc voltsCurrent. 0.15^{□□} ampDirect Interelectrode Capacitances:[○]Grid No.1 to Plate . . . 0.005 max. μf Input. 7 μf Output 6 μf

○ With external shield connected to cathode.

Mechanical:

Mounting Position. Any

Maximum Overall Length 2-25/32"

Maximum Seated Length. 2-1/4"

Maximum Diameter 1-3/16"

Bulb T-9

Base Lock-in 8-Pin

Basing Designation for BOTTOM VIEW 8V

Pin 1-Heater


Pin 2-Plate

Pin 3-Grid No.2

Pin 4-Grid No.3

Pin 5- Internal

Shield



Pin 6-Grid No.1

Pin 7- Cathode

Pin 8- Heater

Plug - Base

Shell

AMPLIFIER - Class A₁**Maximum Ratings, Design-Center Values:**

PLATE VOLTAGE. 300 max. volts

GRID-No.2 (SCREEN) VOLTAGE 300 max. volts

PLATE DISSIPATION. 2 max. watts

GRID-No.2 DISSIPATION. 0.75 max. watt

GRID-No.1 (CONTROL-GRID) VOLTAGE:

Negative bias value. 1 min. volt

PEAK HEATER-CATHODE VOLTAGE:

Heater negative with respect to cathode. 90 max. volts

Heater positive with respect to cathode. 90 max. volts

□ Nominal voltage = 7.0 volts.

□□ Nominal current = 0.16 ampere.

JUNE 15, 1948

TUBE DEPARTMENT

DATA

RADIO CORPORATION OF AMERICA, HARRISON, NEW JERSEY

7AG7



7AG7

SHARP-CUTOFF PENTODE

Typical Operation and Characteristics:

Plate Voltage.	250	. . .	volts
Grid No.3 (Suppressor)	Connected to cathode at socket		
Internal Shield.	Connected to cathode at socket		
Grid-No.2 Voltage.	250	. . .	volts
Cathode-Bias Resistor*	250	. . .	ohms
Plate Resistance (Approx.)	0.75	. . .	megohm
Transconductance	4200	. . .	μ mhos
Grid-No.1 Bias (Approx.) for plate current of 10 μ a	-10	. . .	volts
Plate Current.	6	. . .	ma
Grid-No.2 Current.	2	. . .	ma

* Fixed-bias operation is not recommended.