

Beam Power Tube

DUODECAR TYPE

The 21HJ5 is the same as the 6HJ5 except for the following items:

Heater Characteristics and Ratings:

Current.	0.600 ± 0.040	amp
Voltage (AC or DC) at heater amperes = 0.600	21.5	volts
Warm-up time (Average)	11	sec

22BH3

Half-Wave Vacuum Rectifier

NOVAR TYPE

For TV Damper Service

The 22BH3 is the same as the 6BH3 except for the following items:

Heater Characteristics and Ratings:

Current.	0.450 ± 0.030	amp
Voltage (AC or DC) at heater amperes = 0.450	22.4	volts
Warm-up time (Average)	11	sec

22BH3A

Half-Wave Vacuum Rectifier

NOVAR TYPE

For TV Damper Service

The 22BH3A is the same as the 6BH3A except for the following items:

Heater Characteristics and Ratings:

Current.	0.450 ± 0.030	amp
Voltage (AC or DC) at heater amperes = 0.450	22.4	volts
Warm-up time (Average)	11	sec

