



Current Equipment Type



TYPE EZ80/6V4 MINIATURE FULL-WAVE RECTIFIER



Heater Voltage	6.3 volts
Heater Current	0.6 amp.

RATINGS

Peak Inverse Voltage	980 volts max.
Peak Current (each anode)	270 mA max.
Hot Switching Transient Anode Current	900 mA max.
Peak Heater-Cathode potential	500 volts max.

CHARACTERISTICS AS FULL-WAVE RECTIFIER

CONDENSER INPUT

R.M.S. Input per Anode	...	250	275	300	350 volts
Supply Impedance per Anode	...	125	175	215	300 ohms min.
Reservoir Condenser	...	50	50	50	50 μ F max.
Rectified Current	...	90	90	90	90 mA max.

